Application

Bright Idea LED 180° & 360° street lights can be used in many applications. 360° lamps are ideal for post-top fixtures, bucket lights, and barn lights. Wall packs, canopy lights and floodlights are easily retrofitted with 180° lamps. This very versatile lamp is available in many wattages to meet your needs.

Materials

Bright Idea LED 180° & 360° lamps are constructed with the highest quality materials and components. They are built to last giving you an industry leading 100,000 hours of life*. The lamp housing is made from fire retardant polycarbonate and aluminum alloy is used for the heat sink. The working tempature for our 180° & 360° lamps is rated at -40°F to 176°F.

Installation

Prior to installation, existing ballast must be removed and fixture wired direct. Installation by a licensed electrician is recommended.
















LED 360° Lamps					
Watts	Lumens	Efficacy	Input Voltage	Model No.	Dimensions
12W	1200lm	100lm/W	AC100-300V	SL2-360D-12W	ф2.8 x 6.5in
20W	2100lm	105lm/W	AC100-300V	SL2-360D-20W	ф2.8 x 7.7in
27W	3240lm	120lm/W	AC100-300V	SL2-360D-27W	ф3.7 x 8in
36W	4320lm	120lm/W	AC100-300V	SL2-360D-36W	ф3.7 x 9.2in
45W	5400lm	120lm/W	AC100-300V	SL2-360D-45W	ф3.7 x 10in
54W	6480lm	120lm/W	AC100-300V	SL2-360D-54W	ф3.7 x 10in
60W	7260lm	121lm/W	AC100-300V	SL2-360D-60W-EX	ф4.7 x 9.9in
80W	9680lm	121lm/W	AC100-300V	SL2-360D-80W-EX	ф4.7 x 11.5in
100W	12100lm	121lm/W	AC100-300V	SL2-360D-100W-EX	ф4.7 x 13in
125W	15125lm	121lm/W	AC100-300V	SL2-360D-125W-EX	ф4.7 x 16in
LED 180° Lamps					
20W	2600lm	130lm/W	AC100-277V	SL2-180D-20W	ф3.5 x 7.6in
30W	3930lm	131lm/W	AC100-277V	SL2-180D-30W	ф3.5 x 8.7in
35W	4585lm	131lm/W	AC100-277V	SL2-180D-35W	ф3.5 x 9.3in
40W	5240lm	131lm/W	AC100-277V	SL2-180D-40W	ф3.5 x 10.6in
40W	5240lm	131lm/W	AC100-277V	SL2-180D-40W-EX	ф3.5 x 10.6in
45W	5895lm	131lm/W	AC100-277V	SL2-180D-45W-EX	ф3.5 x 10.8in
50W	6550lm	131lm/W	AC100-277V	SL2-180D-50W-EX	ф3.5 x 10.8in

